

# DENON DJ

## SERATO DIGITAL VINYL AUDIO INTERFACE



FOR THE LOVE OF VINYL

For Pro DJs and Turntablists! Get truly 'hands-on' and control your Serato digital music collection, with the touch and feel of real vinyl records

2-Channel audio interface

Ultra-compact, rugged metal build

Supports Serato NoiseMap™ Control Vinyl and CD



## SOUND CONTROL

Pocket-sized for transport but BIG in musical excellence - rock any bar, club or event with 24-bit, pristine audio

Supports 44.1, 48 and 96kHz sampling rates

Legacy, trusted Denon DJ audio quality

## CONNECT – PLAY – SIMPLE

USB powered and with quick, 'plug-and-play' connectivity, DS1 unlocks Serato DJ Pro for instant DVS control via any DJ mixer

Dual RCA Stereo inputs/outputs

Plays traditional vinyl records too



## Technical Specifications

All specifications are measured at 20 kHz bandwidth.

Line Inputs 1-4 (unbalanced RCA)	
<b>Frequency Response</b>	20 Hz – 20 kHz ( $\pm 0.02$ dB)
<b>Dynamic Range</b>	103 dB (A-weighted)
<b>Signal-to-Noise Ratio</b>	100 dB (1 kHz, +6 dBV (2Vrms), A-weighted)
<b>THD+N</b>	0.002% (1 kHz +6 dBV (2Vrms))
<b>Max Input Level</b>	+9 dBV
<b>Input Impedance</b>	47 k $\Omega$

Phono Inputs 1-4 (unbalanced RCA)	
<b>Dynamic Range</b>	81 dB (A-weighted)
<b>THD+N</b>	0.022% (1 kHz, -27dBV)
<b>Max Input Level</b>	-26dBV (53 mVrms)
<b>Input Impedance</b>	47 k $\Omega$

Line Outputs 1-4 (unbalanced RCA)	
<b>Frequency Response</b>	20 Hz – 20 kHz ( $\pm 0.07$ dB)
<b>Dynamic Range</b>	100 dB (A-weighted)
<b>THD+N</b>	0.007% (1 kHz, -1 dBFS)
<b>Maximum Output Level</b>	+6 dBV
<b>Output Impedance</b>	100 $\Omega$

*Specifications are subject to change without notice.*